



Configuration du modem routeur Pirelli A124G

Client particulier

- Accédez à l'interface du routeur via l'adresse **192.168.1.254**



- Saisissez « **topadmin** » comme login et mot de passe puis cliquez sur « **OK** ».

The image shows a login interface. It consists of two text input fields: one for 'Username' containing 'topadmin' and another for 'Password' containing several blacked-out characters. Below these fields are two buttons: 'LOGIN' and 'CANCEL'. The 'LOGIN' button is highlighted with a red border.

Username:	topadmin
Password:	*****
LOGIN	CANCEL



- Cliquez sur « **WAN** » dans le menu de gauche.

A vertical sidebar menu with a light gray background and dark gray horizontal separators. The menu items are:

- » SETUP WIZARD
- SYSTEM
- WAN**
- » ATM PVC
- » Clone MAC Address
- » DNS
- LAN
- WIRELESS
- NAT
- ROUTING
- FIREWALL
- SNMP
- UPnP
- QoS
- ADSL
- DDNS
- TOOLS
- STATUS

The 'WAN' option is highlighted with a red rectangular box.

WAN Settings

The router can be connected to your service provider in any of the following ways:

ATM PVC
Clone MAC
DNS

To configure ATM VC parameters
To configure WAN Interface MAC Address
To configure DNS



- Cliquez sur « ATM PVC ».

WAN Settings

The router can be connected to your service provider in any of the following ways:

ATM PVC	To configure ATM VC parameters
Clone MAC	To configure WAN Interface MAC Address
DNS	To configure DNS

- Cliquez sur « VC1 ».

ATM PVC

ADSL router uses ATM as its layer 2 protocol. ATM PVC is a virtual connection which acts as a WAN interface. The Gateway supports up to 8 ATM PVCs.

Description	VPI/VCI	Encapsulation	Protocol
VC1	0/35	LLC	PPPoE
VC2	/-	---	---
VC3	/-	---	---
VC4	/-	---	---
VC5	/-	---	---
VC6	/-	---	---
VC7	/-	---	---
VC8	/-	---	---

HELP



- Saisissez le couple **VPI/VCI (0,35)**
- Saisissez votre login de connexion ADSL dans le champ « **Username** » et sélectionnez « **topnet.tn** ».
- Entrez votre mot de passe de connexion ADSL dans le champ « **Password** » et « **confirm Password** ».
- Saisissez **410** dans le champ « **VLAN IDx** ».
- Cliquez sur « **Save SETTINGS** » pour enregistrer la configuration effectuée.

ATM Interface

The screenshot shows the 'ATM Interface' configuration window. Several fields are highlighted with red boxes:

- Protocol: PPPoE
- VPI/VCI: 0 / 35
- Encapsulation: LLC
- QoS Class: UBR
- PCR/SCR/MBS: 4000 / 4000 / 10
- IP assigned by ISP: Yes
- IP Address: 0.0.0
- Subnet Mask: 0.0.0
- Connection Type: Always Connected
- Idle Time: 20 (minutes)
- Authentication Protocol: AUTO
- Connection Retry Timer: 3 (seconds)
- Keepalive Timer: 15 (seconds)
- Username: user (@topnet.tn)
- Password: [REDACTED]
- Confirm Password: [REDACTED]
- MTU: 1492
- VLAN IDx: 410 (G-66506)

At the bottom right are three buttons: HELP, SAVE SETTINGS (highlighted with a red box), and CANCEL.



- Patientez durant l'enregistrement des informations sur le routeur.

